

- 1. Download X-Lite from the developer (free)
- 2. <u>http://www.counterpath.com/xlitedownload/</u>
 - 3. Set the X-Lite on your computer
 - 1. Run the downloaded executable file (double-click)
 - 2. Follow the instructions of the installer
- 4. Start X-Lite

If you have activated brandmaueer Windows, when you first start the program will be a security warning . To allow access to the Internet softphone , you need to click the " Unblock " .



4. The first time you should see a screen **SIP Accounts.**

Enabled	Acct #	Domain	Username	Display Name	<u>A</u> dd
	1				Remove
					Properties
					Make <u>D</u> efault

If it does not , click on the menu item SIP Accounts Settings ...



4. In the **SIP Accounts** click on the button **Add** ..., which opens the settings window **SIP account**

iccount	Voicemail	Topology	Security	Advanced							
User D	etails										
Display Name			SIPLogin								
User name Password Authorization user name Domain			SIPLogin ••••• SIPLogin sip.kittelecom.co								
						Domai	n Proxy				
						Reg	gister with o	domain and r	eceive inco	oming calls	
						Send outbound via:					
с											
0	proxy	Address									
0	target dom	ain									
Dialing plan											

5. In the **SIP** account settings , complete the following fields: Display name - any name (only latin letters) User name - your user name (obtained from Kittelecom) Password - your password (obtained from the service desk flagmantelecom.ru) o Authorization user name - the same as User name Domain - server name (sip.kittelecom.co) Register with domain and receive incoming calls - set a bird) Dialing plan - remove the contents and leave empty.

6. In the **SIP** account settings press the button **Ok**.

7. In the SIP Accounts click click Close.
8. X-Lite has to register with the network kittelecom.co then X-Lite is ready for use .

